

BIG-IP[®] System and SafeNet Luna SA HSM: Implementation

Version 13.0



Table of Contents

Implementing the SafeNet Luna HSM with BIG-IP Systems.....	5
Overview: Setting up the SafeNet Luna SA HSM with BIG-IP systems, using a script.....	5
Prerequisites for setting up SafeNet Luna SA HSM with BIG-IP systems.....	5
Task summary.....	6
Preparing to install the Luna SA client on the BIG-IP system.....	6
Installing and registering the Luna SA client.....	6
Setting up the Luna SA client on a newly added or activated blade.....	7
Generating a key/certificate using tmsh.....	7
Generating a key/certificate using the fipskey.nethsm utility.....	8
Creating a client SSL profile to use an external HSM key and certificate	9
Manually Setting Up the SafeNet Luna HSM with BIG-IP Systems.....	11
Overview: Manually setting up the SafeNet Luna SA HSM with BIG-IP systems	11
Prerequisites for setting up SafeNet Luna SA HSM with BIG-IP systems.....	11
Task summary.....	12
Preparing to manually install the Luna SA client on the BIG-IP system.....	12
Manually installing and registering the Luna SA client.....	12
Generating a key/certificate using tmsh.....	15
Generating a key/certificate using the fipskey.nethsm utility.....	16
Creating a client SSL profile to use an external HSM key and certificate	17
Additional Information.....	19
Upgrading the BIG-IP software when using the SafeNet Luna HSM.....	19
Uninstalling SafeNet Luna SA components from the BIG-IP system.....	19
nethsm-safenet-install.sh utility options.....	19
Legal Notices.....	21
Legal notices.....	21

Implementing the SafeNet Luna HSM with BIG-IP Systems

Overview: Setting up the SafeNet Luna SA HSM with BIG-IP systems, using a script

The SafeNet Luna SA HSM is an external hardware security module that is available for use with BIG-IP® systems. Because it is network-based, you can use the SafeNet solution with all BIG-IP platforms, including VIPRION® Series chassis and appliances and BIG-IP Virtual Edition (VE). You can also configure multiple HSMs as an HA (high availability) group to use with BIG-IP systems.

Note: The BIG-IP system does not support the SafeNet Luna SA HSM in Appliance mode.

Only RSA-based cipher suites use the network HSM. After installation on the BIG-IP system, the SafeNet Luna SA HSM is compatible with Access Policy Manager® and Application Security Manager™, without additional configuration steps.

Note: This implementation describes the steps for using an installation script. If the installation script does not support your network configuration, refer to the procedure for manual setup.

For information about using the iControl® interface to configure the Luna SA HSM with BIG-IP systems, consult the F5 DevCentral site (<https://devcentral.f5.com/icontrol/>).

For additional information about using the Luna SA HSM, contact SafeNet Technical Support (<http://www.safenet-inc.com/technical-support/>).

Prerequisites for setting up SafeNet Luna SA HSM with BIG-IP systems

Before you can use SafeNet Luna SA HSM with the BIG-IP® system, you must make sure that:

- The SafeNet device is installed on your network.
- The SafeNet device and the BIG-IP system can communicate with each other.
- The SafeNet device has a virtual HSM (HSM Partition) defined before you install the client software on the BIG-IP system.
- The BIG-IP system is licensed for external interface and network HSM.

Additionally, before you begin the installation process, make sure that you have access to:

- The Luna SA Client software. See the *Interoperability Matrix for BIG-IP TMOS with SafeNet Clients and HSM* supplemental document available on AskF5 for supported SafeNet client and HSM versions with BIG-IP TMOS versions information.
- The Luna SA Customer Documentation.

Note: If you install the Luna SA HSM (external HSM) on a system with a FIPS card (internal HSM) installed, the Luna SA HSM takes precedence. You cannot use the SafeNet Luna SA HSM on a BIG-IP system that is running another external HSM.

Note: BIG-IP TMOS with SafeNet Luna SA HSM only supports IPv4.

Task summary

The implementation process involves preparation of the SafeNet device and the BIG-IP[®] system, followed by key/certificate management and creation of a client SSL profile to use the key and certificate. You can generate SafeNet HSM protected keys and corresponding CSR and certificate using either `tmsh` (recommended) or the `fipskey.nethsm` utility.

Task list

Preparing to install the Luna SA client on the BIG-IP system

Installing and registering the Luna SA client

Setting up the Luna SA client on a newly added or activated blade

Generating a key/certificate using `tmsh`

Generating a key/certificate using the `fipskey.nethsm` utility

Creating a client SSL profile to use an external HSM key and certificate

Preparing to install the Luna SA client on the BIG-IP system

Before you can set up the SafeNet Luna SA client software on a BIG-IP[®] system, you must obtain a valid SafeNet Luna SA client license.

To use the Luna SA HSM, you need to obtain the software tarball from SafeNet, and install the Luna SA client software onto the BIG-IP system.

1. Log in to the SafeNet Support portal.

`https://serviceportal.safenet-inc.com`

2. Download the appropriate document, using the download password `F5Clientdownload!`.

***Note:** For supported SafeNet client and HSM versions with BIG-IP TMOS versions information, see the *Interoperability Matrix for BIG-IP TMOS with SafeNet Clients and HSM* supplemental document available on AskF5.*

3. Log in to the command-line interface of the BIG-IP system using an account with administrator privileges.
4. Create a directory under `/shared` named `safenet_install`.
`mkdir /shared/safenet_install`
5. Copy the software tarball to `/shared/safenet_install`.

Installing and registering the Luna SA client

You install and register the Luna SA client so that you can use the Luna SA device with the BIG-IP[®] system. You provide the passwords for your Luna SA device during the installation process. If you are setting up the Luna SA client on a VIPRION[®] system, you run the configuration script only on the primary blade, and then the system propagates the configuration to the additional active blades.

1. Log in to the command-line interface of the system using administrator privileges.
2. If you are installing the Luna SA client on a VIPRION system, and you are using the management network to connect to the HSM, disable `ip check` on the HSM. If you are not installing on a VIPRION system, or you are using a self IP address to communicate with the HSM, skip this step.

```
tls ipcheck disable
service restart ntl
```

This step allows the same certificate to be used from multiple IP addresses, identifying multiple blades.

3. Install and register the Luna SA client on the BIG-IP system, using the parameters indicated.

```
nethsm-safenet-install.sh
```

- Parameters for a typical installation or on the primary blade of a VIPRION system.

```
--hsm_ip_addr=<luna_sa_device_IP_address>  
[--image=<Luna_x.x_Client_Software.tar>]
```

The following example sets up the version 5.2 client where the Luna SA device has an IP address of 172.27.13.59:

```
nethsm-safenet-install.sh --hsm_ip_addr=172.27.13.59 --  
image=Luna_5.2_Client_Software.tar
```

Note: The VIPRION system propagates the configuration to additional active blades, but you need to reload the PATH environment variable on any blades with already-open sessions: `source ~/.bash_profile`

- Parameters when multiple HSMs are configured as an HA group.

```
--hsm_ip_addr="<SafeNet_HSM1_IP_address> <SafeNet_HSM2_IP_address>"  
--hsm_ha_group=<Label name for the SafeNet HSM HA group>]  
[--image=<Luna_x.x_Client_Software.tar>]
```

The following example sets up the version 5.2 client for an HA group named `luna_ha_test` where the Luna SA devices in the group have IP addresses of 10.10.10.100 and 10.10.10.101:

```
nethsm-safenet-install.sh --hsm_ip_addr="10.10.10.100 10.10.10.101" --  
hsm_ha_group=luna_ha_test --image=Luna_5.2_Client_Software.tar
```

Install all components when prompted. During the installation, you will register your client IP address with the SafeNet device and assign the Luna SA client to a previously defined HSM partition. For an HA configuration, this must be the first slot.

Note: By default, the script sets up the SafeNet Luna SA client software to use 20 threads. To adjust this number, run this command before you restart the `pkcs11d` service: `tmssh sys crypto fips external-hsm num-threads <integer>`. Changing the number of threads affects performance.

Setting up the Luna SA client on a newly added or activated blade

After you set up the Luna SA client on the primary blade of a VIPRION[®] system, the system propagates the configuration to the additional active blades. If you subsequently add a secondary blade, activate a disabled blade, or power-on a powered-off blade, you need to run a script on the new secondary blade.

1. Log in to the command-line interface of the system using an account with administrator privileges.
2. Run this script on any new or re-activated secondary blade:


```
safenet-sync.sh <HSM partition password> -v
```
3. If you make the new blade a primary blade before running the synchronization script, you need to run the regular client installation and registration procedure on the new primary blade only.

```
nethsm-safenet-install.sh
```

Generating a key/certificate using tmssh

You can use the Traffic Management Shell (`tmssh`) to generate a key and certificate.

1. Log in to the command-line interface of the system using an account with administrator privileges.
2. Open the Traffic Management Shell (tmsh).

```
tmsh
```

3. Generate the key.

```
create sys crypto key <key_name> gen-certificate common-name <cert_name>
security-type nethsm
```

This example generates an external HSM key named `test_key` and a certificate named `test_safenet.com` with the security type of `nethsm`:

```
create sys crypto key test_key gen-certificate common-name test_safenet.com
security-type nethsm
```

4. Verify that the key was created.

```
list sys crypto key siterequest.key
```

Information about the key displays:

```
sys crypto key siterequest.key {
key-size 2048
key-type rsa-private
security-type nethsm
}
```

When you generate a key/certificate using `tmsh`, the system also creates a local key, which points to the HSM key, residing in the HSM.

Generating a key/certificate using the `fipskey.nethsm` utility

Before you generate a key/certificate, make sure that the SafeNet Luna SA client is running on the BIG-IP® system.

You can use the `fipskey.nethsm` utility to generate private keys and self-signed certificates on the BIG-IP system.

1. Display the available options.

```
fipskey.nethsm --help
```

2. Generate the key, using any options you need.

```
fipskey.nethsm --genkey -o <output_file>
```

This example generates the three files that follow:

```
fipskey.nethsm --genkey -o siterequest
```

- `/config/ssl/ssl.key/siterequest.key`
- `/config/ssl/ssl.csr/siterequest.csr`
- `/config/ssl/ssl.crt/siterequest.crt`

The key is saved in `/config/ssl/ssl.key/<output_file>.key`. The certificate request is saved in `/config/ssl/ssl.csr/<output_file>.csr`. The self-signed certificate is saved in `/config/ssl/ssl.crt/<output_file>.crt`.

After you generate keys and certificates, you need to add the local key to the BIG-IP configuration using `tmsh`. The local key points to the HSM key, which resides in the HSM.

Adding the SafeNet local key to the BIG-IP system configuration

You can use the Traffic Management Shell (`tmsh`) to add the SafeNet local key, which was created on the BIG-IP® system when you generated a key/certificate using the `fipskey.nethsm` utility. The local key points to the HSM key.

1. Log in to the command-line interface of the system using an account with administrator privileges.
2. Open the Traffic Management Shell (tmsh).

```
tmsh
```

3. Add the key.

```
install sys crypto key key_object_name< from-local-file keyname>
```

This example adds a local key named `my_key.key` from a local key file stored in the `/config/ssl/ssl.key/` directory: `install sys crypto key my_key.key from-local-file /config/ssl/ssl.key/my_key.key`

Adding certificates using tmsh

You can use the Traffic Management Shell (tmsh) to add existing certificates to the BIG-IP® system configuration.

1. Log in to the command-line interface of the system using an account with administrator privileges.
2. Open the Traffic Management Shell (tmsh).

```
tmsh
```

3. Add the certificate.

```
install sys crypto cert cert_object_name from-local-file  
path_to_cert_file
```

This example loads the certificate named `my_key.crt` from a local certificate file stored in the `/config/ssl/ssl.crt/` directory:

```
install sys crypto cert my_key.crt from-local-file /config/ssl/ssl.crt/  
my_key.crt
```

Creating a client SSL profile to use an external HSM key and certificate

After you have added the external HSM key and certificate to the BIG-IP® system configuration, you can use the key and certificate as part of a client SSL profile. This task describes using the browser interface. Alternatively, you can use the Traffic Management Shell (tmsh) command-line utility.

1. On the Main tab, click **Local Traffic > Profiles > SSL > Client**.
The Client screen opens.
2. Click **Create**.
The New Client SSL Profile screen opens.
3. In the **Name** field, type a name for the profile.
4. From the **Parent Profile** list, select **clientssl**.
5. From the **Configuration** list, select **Advanced**.
This selection makes it possible for you to modify additional default settings.
6. For the Configuration area, select the **Custom** check box.
The settings in the Configuration area become available for modification.
7. Using the **Certificate Key Chain** setting, specify one or more certificate key chains:
 - a) From the **Certificate** list, select the name of a certificate that you imported.
 - b) From the **Key** list, select the name of the key that you imported.
 - c) From the **Chain** list, select the chain that you want to include in the certificate key chain.
 - d) Click **Add**.
8. Click **Finished**.

After you have created the client SSL profile, you must assign the profile to a virtual server, so that the virtual server can process SSL traffic according to the specified profile settings.

Manually Setting Up the SafeNet Luna HSM with BIG-IP Systems

Overview: Manually setting up the SafeNet Luna SA HSM with BIG-IP systems

The SafeNet Luna SA HSM is an external hardware security module that is available for use with BIG-IP® systems. Because it is network-based, you can use the SafeNet solution with all BIG-IP platforms, including VIPRION® Series chassis and appliances and BIG-IP Virtual Edition (VE). You can also configure multiple HSMs as an HA (high availability) group to use with BIG-IP systems. Typically, you would use the script to set up the SafeNet Luna SA HSM. However, in cases where the installation script does not support your network configuration, you can install one or more HSMs manually. For a VIPRION Series chassis, this procedure would require manual setup on the additional blades.

Note: The BIG-IP system does not support the SafeNet Luna SA HSM in Appliance mode.

Only RSA-based cipher suites use the network HSM. After installation on the BIG-IP system, the SafeNet Luna SA HSM is compatible with Access Policy Manager® and Application Security Manager™, without additional configuration steps.

For information about using the iControl® interface to configure the Luna SA HSM with BIG-IP systems, consult the F5 DevCentral site (<https://devcentral.f5.com/icontrol/>).

For additional information about using the Luna SA HSM, contact SafeNet Technical Support (<http://www.safenet-inc.com/technical-support/>).

Prerequisites for setting up SafeNet Luna SA HSM with BIG-IP systems

Before you can use SafeNet Luna SA HSM with the BIG-IP® system, you must make sure that:

- The SafeNet device is installed on your network.
- The SafeNet device and the BIG-IP system can communicate with each other.
- The SafeNet device has a virtual HSM (HSM Partition) defined before you install the client software on the BIG-IP system.
- The BIG-IP system is licensed for external interface and network HSM.

Additionally, before you begin the installation process, make sure that you have access to:

- The Luna SA Client software. See the *Interoperability Matrix for BIG-IP TMOS with SafeNet Clients and HSM* supplemental document available on AskF5 for supported SafeNet client and HSM versions with BIG-IP TMOS versions information.
- The Luna SA Customer Documentation.

Note: If you install the Luna SA HSM (external HSM) on a system with a FIPS card (internal HSM) installed, the Luna SA HSM takes precedence. You cannot use the SafeNet Luna SA HSM on a BIG-IP system that is running another external HSM.

Note: BIG-IP TMOS with SafeNet Luna SA HSM only supports IPv4.

Task summary

The implementation process for a manual installation involves preparation of the SafeNet device and the BIG-IP[®] system, followed by key/certificate management and creation of a client SSL profile to use the key and certificate. If you are setting up multiple HSMs configured as an HA group, you repeat a subset of the manual installation steps for each additional HSM, and then create an HA group. You can generate SafeNet HSM protected keys and corresponding CSR and certificate using either `tmsh` (recommended) or the `fipskey.nethsm` utility.

Task list

Preparing to manually install the Luna SA client on the BIG-IP system

Manually installing and registering the Luna SA client

Generating a key/certificate using `tmsh`

Generating a key/certificate using the `fipskey.nethsm` utility

Creating a client SSL profile to use an external HSM key and certificate

Preparing to manually install the Luna SA client on the BIG-IP system

Before you can set up the SafeNet Luna SA client software on a BIG-IP[®] system, you must obtain a valid SafeNet Luna SA client license.

To use the Luna SA HSM, you need to obtain the software tarball from SafeNet, and install the Luna SA client software onto the BIG-IP system.

1. Log in to the SafeNet Support portal.

```
https://serviceportal.safenet-inc.com
```

2. Download the appropriate document, using the download password `F5Clientdownload!`.

***Note:** For supported SafeNet client and HSM versions with BIG-IP TMOS versions information, see the *Interoperability Matrix for BIG-IP TMOS with SafeNet Clients and HSM supplemental document* available on AskF5.*

3. Log in to the command-line interface of the BIG-IP system using an account with administrator privileges.

4. Create a directory under `/shared` named `safenet_install`.

```
mkdir /shared/safenet_install
```

5. Copy the software tarball to `/shared/safenet_install`.

Manually installing and registering the Luna SA client

You install and register the Luna SA client so that you can use the Luna SA device with the BIG-IP[®] system. You provide the passwords for your Luna SA device during the installation process. You can use this procedure to install and register the Luna SA client on the BIG-IP system, either for a single HSM or multiple HSMs configured as an HA group.

1. If you are installing the Luna SA client on a VIPRION system, and you are using the management network to connect to the HSM, disable `ip check` on the HSM. If you are not installing on a VIPRION system, or you are using a self IP address to communicate with the HSM, skip this step.

```
tls ipcheck disable
service restart ntl
```

This step allows the same certificate to be used from multiple IP addresses, identifying multiple blades.

2. Untar the image, and place the extracted files into appropriate directories, moving the extracted toolkit to the safenet path.

```
tar -C /shared/safenet_install -xvr /shared/safenet_install/<lunasa tar file>
mkdir -p /shared/safenet/toolkit
mv /shared/safenet_install/toolkit/* /shared/safenet/toolkit
chmod 755 /shared/safenet/toolkit/*
```

3. Set the write permission and create softlinks for the /usr path.

```
mount -o remount,rw /usr    mkdir -p /shared/safenet/lunasa
rm -rf /usr/lunasa
ln -sf /shared/safenet/lunasa /usr/lunasa

rm -rf /usr/safenet/
mkdir -p /usr/safenet/
ln -sf /shared/safenet/lunasa /usr/safenet/lunaclient
```

4. Install the SafeNet Luna SA package.

```
sh /shared/safenet_install/linux/x86/64/install.sh
```

5. Adjust the location and permission of the Chrystoki.conf file

```
mv /etc/Chrystoki.conf /shared/safenet/lunasa/Chrystoki.conf
restorecon /shared/safenet/lunasa/Chrystoki.conf
chmod 644 /shared/safenet/lunasa/Chrystoki.conf
```

6. Add these entries to the file /shared/safenet/lunasa/Chrystoki.conf, if the entries do not already exist:

```
Misc = {
    Apache = 0;
    PE1746Enabled=1;
}

EngineLunaCA3 = {
    DisableCheckFinalize = 1;
    DisableEcdsa = 0;
    DisableDsa = 0;
    DisableRand = 0;
    EngineInit = 1:10:11;
    LibPath64 = /usr/lunasa/lib/libCryptoki2_64.so;
    LibPath = /usr/lunasa/lib/libCryptoki2.so;
}
```

7. Set these softlinks:

```
ln -sf /shared/safenet/lunasa/Chrystoki.conf /etc/Chrystoki.conf
ln -sf /shared/safenet/lunasa/lib/libCryptoki2_64.so /usr/lib/libCryptoki2_64.so
```

8. Fetch the server certificate from the SafeNet Luna SA HSM.

```
scp <hsm_username>@<hsm_ip_addr>:server.pem /usr/lunasa/bin/server_<hsm_ip_addr>.pem
```

9. Create the client certificate.

```
/usr/lunasa/bin/vtl createCert -n <BIG-IP IP address>
```

10. Send the client certificate to the SafeNet Luna SA HSM.

```
scp /usr/lunasa/cert/client/<BIG-IP IP address>.pem <hsm_username>@<hsm_ip_addr>:
```

11. Clean up the old server information (if any), and add the server information to the client.

Manually Setting Up the SafeNet Luna HSM with BIG-IP Systems

```
/usr/lunasa/bin/vtl deleteServer -n <hsm_ip_addr>
rm -f /usr/lunasa/cert/server/CAFile.pem
rm -f /usr/lunasa/cert/server/<hsm_ip_addr>Cert.pem
```

12. Add the server to the list of servers.

```
/usr/lunasa/bin/vtl addServer -n <hsm_ip_addr> -c /usr/lunasa/bin/server_<hsm_ip_addr>.pem
```

13. On the SafeNet Luna SA HSM device, register a client name that has the IP address of the BIG-IP system, and assign a partition for the client.

```
lunash:> client register -client <clientname> [-hostname <resolvable hostname>] [-ip
<client IP address>]
lunash:> client assignPartition -client <clientname> -partition <partitionname>
```

For additional details, refer to the SafeNet documentation.

14. (HA only) If you are setting up multiple HSMs configured as an HA group, repeat these steps for each SafeNet Luna SA HSM device.

a) Fetch the server certificate from the Safenet Luna SA HSM.

```
scp <hsm_username>@<hsm_ip_addr>:server.pem /usr/lunasa/bin/server_<hsm_ip_addr>.pem
```

b) Send the client certificate to the SafeNet Luna SA HSM.

```
scp /usr/lunasa/cert/client/<BIG-IP IP address>.pem <hsm_username>@<hsm_ip_addr>:
```

c) Clean up the old server information (if any), and add the server information to the client.

```
/usr/lunasa/bin/vtl deleteServer -n <hsm_ip_addr>
rm -f /usr/lunasa/cert/server/<hsm_ip_addr>Cert.pem
```

d) Add the server to the list of servers.

```
/usr/lunasa/bin/vtl addServer -n <hsm_ip_addr> -c /usr/lunasa/bin/server_<hsm_ip_addr>.pem
```

e) On the SafeNet Luna SA HSM device, register a client name that has the IP address of the BIG-IP system, and assign a partition for the client.

```
lunash:> client register -client <clientname> [-hostname <resolvable hostname>] [-ip
<client IP address>]
lunash:> client assignPartition -client <clientname> -partition <partitionname>
```

For additional details, refer to the SafeNet documentation.

This example shows the list of slots after the BIG-IP system is securely connected to two SafeNet Luna SA HSMs.

```
[root@test:Active:Standalone] shared # vtl listSlots
Number of slots: 5
```

The following slots were found:

Slot #	Description	Label	Serial #	Status
slot #1	LunaNet Slot	test1	153124004	Present
slot #2	LunaNet Slot	test1	153560010	Present
slot #3	-	-	-	Not present
slot #4	-	-	-	Not present
slot #5	-	-	-	Not present

15. (HA only) If you are setting up multiple HSMs configured as an HA group, after you have securely connected all the SafeNet Luna SA HSMs, create an HA group, and add all the HSMs into the group. These commands use serial numbers from the previous example.

```
/usr/lunasa/bin/vtl haAdmin newGroup -serialNum 153124004 -label ha1
/usr/lunasa/bin/vtl haAdmin addMember -group ha1 -serialNum 153560010
/usr/lunasa/bin/vtl haAdmin HAOnly -enable
```

16. (HA only) Verify that the HA group configuration was successful.

```
/usr/lunasa/bin/vtl listSlots
```

17. Close and open the session for the SafeNet Luna SA HSM in slot #1.

```
/shared/safenet/toolkit/sautil -v -s 1 -i 10:11 -c
/shared/safenet/toolkit/sautil -v -s 1 -i 10:11 -o -p <hsm_partition_password>
```

18. Install the pkcs11d service on the BIG-IP system.

```
bigstart add pkcs11d
bigstart stop pkcs11d
bigstart add --default pkcs11d
```

19. Revert the read-write permission.

```
mount -o remount,ro /usr
```

20. Set the vendor name to SafeNet.

```
fipskey.nethsm --hsm=SafeNet
```

21. Configure the vendor name and partition password in tmsh.

```
tmsh create sys crypto fips external-hsm vendor safenet password <SafeNet partition password>
```

22. To adjust the number of threads, you can modify the configuration, as shown.

```
tmsh modify sys crypto fips external-hsm num-threads <integer>
```

The default value for the number of threads is 20.

23. Restart the daemons.

- a) Restart the pkcs11d service.

```
bigstart restart pkcs11d
```

- b) Restart tmm.

```
bigstart restart tmm
```

Generating a key/certificate using tmsh

You can use the Traffic Management Shell (tmsh) to generate a key and certificate.

1. Log in to the command-line interface of the system using an account with administrator privileges.
2. Open the Traffic Management Shell (tmsh).

```
tmsh
```

3. Generate the key.

```
create sys crypto key <key_name> gen-certificate common-name <cert_name>
security-type nethsm
```

This example generates an external HSM key named `test_key` and a certificate named `test_safenet.com` with the security type of `nethsm`:

```
create sys crypto key test_key gen-certificate common-name test_safenet.com
security-type nethsm
```

4. Verify that the key was created.

```
list sys crypto key siterequest.key
```

Information about the key displays:

```
sys crypto key siterequest.key {  
key-size 2048  
key-type rsa-private  
security-type nethsm  
}
```

When you generate a key/certificate using `tmsh`, the system also creates a local key, which points to the HSM key, residing in the HSM.

Generating a key/certificate using the `fipskey.nethsm` utility

Before you generate a key/certificate, make sure that the SafeNet Luna SA client is running on the BIG-IP® system.

You can use the `fipskey.nethsm` utility to generate private keys and self-signed certificates on the BIG-IP system.

1. Display the available options.

```
fipskey.nethsm --help
```

2. Generate the key, using any options you need.

```
fipskey.nethsm --genkey -o <output_file>
```

This example generates the three files that follow:

```
fipskey.nethsm --genkey -o siterequest
```

- `/config/ssl/ssl.key/siterequest.key`
- `/config/ssl/ssl.csr/siterequest.csr`
- `/config/ssl/ssl.crt/siterequest.crt`

The key is saved in `/config/ssl/ssl.key/<output_file>.key`. The certificate request is saved in `/config/ssl/ssl.csr/<output_file>.csr`. The self-signed certificate is saved in `/config/ssl/ssl.crt/<output_file>.crt`.

After you generate keys and certificates, you need to add the local key to the BIG-IP configuration using `tmsh`. The local key points to the HSM key, which resides in the HSM.

Adding the SafeNet local key to the BIG-IP system configuration

You can use the Traffic Management Shell (`tmsh`) to add the SafeNet local key, which was created on the BIG-IP® system when you generated a key/certificate using the `fipskey.nethsm` utility. The local key points to the HSM key.

1. Log in to the command-line interface of the system using an account with administrator privileges.
2. Open the Traffic Management Shell (`tmsh`).

```
tmsh
```

3. Add the key.

```
install sys crypto key <key_object_name>< from-local-file <keyname>
```

This example adds a local key named `my_key.key` from a local key file stored in the `/config/ssl/ssl.key/` directory: `install sys crypto key my_key.key from-local-file /config/ssl/ssl.key/my_key.key`

Adding certificates using `tmsh`

You can use the Traffic Management Shell (`tmsh`) to add existing certificates to the BIG-IP® system configuration.

1. Log in to the command-line interface of the system using an account with administrator privileges.
2. Open the Traffic Management Shell (`tmsh`).


```
tmsb
```

3. Add the certificate.

```
install sys crypto cert <cert_object_name> from-local-file
<path_to_cert_file>
```

This example loads the certificate named `my_key.crt` from a local certificate file stored in the `/config/ssl/ssl.crt/` directory:

```
install sys crypto cert my_key.crt from-local-file /config/ssl/ssl.crt/
my_key.crt
```

Creating a client SSL profile to use an external HSM key and certificate

After you have added the external HSM key and certificate to the BIG-IP® system configuration, you can use the key and certificate as part of a client SSL profile. This task describes using the browser interface. Alternatively, you can use the Traffic Management Shell (`tmsb`) command-line utility.

1. On the Main tab, click **Local Traffic > Profiles > SSL > Client.**

The Client screen opens.

2. Click **Create.**

The New Client SSL Profile screen opens.

3. In the **Name field, type a name for the profile.**

4. From the **Parent Profile list, select **clientssl**.**

5. From the **Configuration list, select **Advanced**.**

This selection makes it possible for you to modify additional default settings.

6. For the Configuration area, select the **Custom check box.**

The settings in the Configuration area become available for modification.

7. Using the **Certificate Key Chain setting, specify one or more certificate key chains:**

a) From the **Certificate** list, select the name of a certificate that you imported.

b) From the **Key** list, select the name of the key that you imported.

c) From the **Chain** list, select the chain that you want to include in the certificate key chain.

d) Click **Add**.

8. Click **Finished.**

After you have created the client SSL profile, you must assign the profile to a virtual server, so that the virtual server can process SSL traffic according to the specified profile settings.

Additional Information

Upgrading the BIG-IP software when using the SafeNet Luna HSM

After a BIG-IP® system software or hotfix upgrade, you must run the SafeNet Luna SA client setup script to restore your default SafeNet configuration. Any local keys and certificates you added to the BIG-IP system configuration before upgrading (using the command `tmsh install sys crypto`) appear in the upgrade partition, but they are usable only after you run the SafeNet Luna SA client setup script. Keys, certificates, and CSRs created using `tmsh` are already part of the BIG-IP system configuration, and can be used after running the SafeNet script. If you are restoring the Luna SA client on a VIPRION® system, you run the script only on the primary blade, and then the system propagates the configuration to the additional active blades.

***Note:** If you will need keys, certificates, or CSRs that were not added to the BIG-IP system configuration, before you upgrade, copy the files into the `/shared` directory. After the upgrade, copy them back to their appropriate directories in the new partition: `/config/ssl/ssl.key/`, `/config/ssl/ssl.crt`, or `/config/ssl/ssl.csr`.*

1. Log in to the command-line interface of the BIG-IP system using an account with administrator privileges.
2. Reinstall the Luna SA client on the BIG-IP system, using the parameters you used when you initially installed and registered it.

```
nethsm-safenet-install.sh
```

Uninstalling SafeNet Luna SA components from the BIG-IP system

If you no longer need to use the SafeNet Luna SA HSM on a BIG-IP® system, you should uninstall the files.

1. Log in to the command-line interface of the system using an account with administrator privileges.
2. Uninstall the SafeNet client software and clean up SafeNet directories.

```
nethsm-safenet-install.sh -u [-v]
```

nethsm-safenet-install.sh utility options

The `nethsm-safenet-install.sh` utility includes these options:

Option	Description
<code>-h</code>	Display help
<code>-v</code>	Verbose output
<code>--</code>	SafeNet
<code>hsm_ip</code>	Luna SA
<code>_addr=</code>	HSM IP
<code><ip_ad</code>	address
<code>dr></code>	

Option	Description
-- hsm_username=<user_name>	SafeNet Luna SA HSM user name. Default is admin.
-- interface_name=<interface_name>	BIG-IP system interface used to communicate with the SafeNet Luna SA HSM. Default is the management interface.
-- client_ip_address=<client_ip_address>	IP address of the BIG-IP system, as seen by the SafeNet Luna SA HSM
-- hsm_password=<password>	SafeNet Luna SA HSM partition password
-- image=<image_name>	SafeNet Luna SA tarball to be installed (for example, Luna_5.1_Client_Software.tar). This file must be stored on the BIG-IP system in /shared/safenet_install.

Legal Notices

Legal notices

Publication Date

This document was published on May 25, 2017.

Publication Number

MAN-0496-04

Copyright

Copyright © 2017, F5 Networks, Inc. All rights reserved.

F5 Networks, Inc. (F5) believes the information it furnishes to be accurate and reliable. However, F5 assumes no responsibility for the use of this information, nor any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent, copyright, or other intellectual property right of F5 except as specifically described by applicable user licenses. F5 reserves the right to change specifications at any time without notice.

Trademarks

For a current list of F5 trademarks and service marks, see <http://www.f5.com/about/guidelines-policies/trademarks>.

All other product and company names herein may be trademarks of their respective owners.

Patents

This product may be protected by one or more patents indicated at: <https://f5.com/about-us/policies/patents>.

Link Controller Availability

This product is not currently available in the U.S.

Export Regulation Notice

This product may include cryptographic software. Under the Export Administration Act, the United States government may consider it a criminal offense to export this product from the United States.

RF Interference Warning

This is a Class A product. In a domestic environment this product may cause radio interference, in which case the user may be required to take adequate measures.

FCC Compliance

This equipment has been tested and found to comply with the limits for a Class A digital device pursuant to Part 15 of FCC rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This unit generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a

Legal Notices

residential area is likely to cause harmful interference, in which case the user, at his own expense, will be required to take whatever measures may be required to correct the interference.

Any modifications to this device, unless expressly approved by the manufacturer, can void the user's authority to operate this equipment under part 15 of the FCC rules.

Canadian Regulatory Compliance

This Class A digital apparatus complies with Canadian ICES-003.

Standards Compliance

This product conforms to the IEC, European Union, ANSI/UL and Canadian CSA standards applicable to Information Technology products at the time of manufacture.

Index

B

BIG-IP system software upgrade
restoring SafeNet client configuration 19

C

certificates
adding using tmsh 9, 16
generating for use with BIG-IP 8, 16
generating using tmsh 7, 15
client installation
preparing Luna SA 6
client manual installation
preparing for Luna SA 12
client SSL profile
using with external HSM key and certificate 9, 17

E

external HSM
about manual set up 11
about script setup 5
overview of manual setup implementation 11
overview of script setup 5
using key and certificate with client SSL profile 9, 17
with BIG-IP Virtual Edition (VE) 5, 11

F

FIPS card
using with external HSM 5, 11
FIPS key, *See* external HSM key.
fipskey.nethsm utility
generating certificates 8, 16
generating keys 8, 16

H

hardware security module (HSM)
external 5, 11
HSM Partition
assigning client to 6, 12
defining 5, 11

I

implementation
task summary 6, 12
installation
for Luna SA client 6, 12
internal HSM, *See* FIPS card.

K

key
generating for use with BIG-IP 8, 16

key (*continued*)
generating using tmsh 7, 15

L

Luna SA client
generating certificates 8, 16
generating keys 8, 16
installing 6, 12
installing on added blade 7
preparing for installation 6
preparing for manual installation 12
registering 6, 12
uninstalling 19

N

nethsm-safenet-install.sh utility
installing the Luna SA client 6
options 19
registering the Luna SA client 6

P

preparation
for installing Luna SA client 6, 12
prerequisites for set up 5, 11

R

registration
for Luna SA client 6, 12

S

SafeNet HSM
implementing with BIG-IP Systems 5, 11
restoring client on upgraded BIG-IP system 19
SafeNet local key
adding with tmsh 8, 16

T

tmsh commands
adding certificates 9, 16
adding SafeNet local key 8, 16
generating certificates 7, 15
generating keys 7, 15

V

virtual HSM, *See* HSM Partition.

