

BIG-IP[®] Virtual Edition and Linux Xen Project: Setup

Version 12.1



Table of Contents

Getting Started with BIG-IP Virtual Edition on Xen Project.....	5
Steps to deploy BIG-IP VE.....	5
Prerequisites for BIG-IP Virtual Edition on Xen Project.....	7
Host CPU requirements.....	7
Host memory requirements.....	7
Configuring SR-IOV on the hypervisor.....	7
Virtual machine memory requirements.....	7
Virtual machine storage requirements.....	8
Virtual machine network interfaces.....	8
Deploying BIG-IP Virtual Edition in Xen Project.....	9
Deploying BIG-IP VE on Xen Project.....	9
Accessing the BIG-IP VE management user interface.....	10
After Deploying BIG-IP VE on Xen Project.....	11
About licensing BIG-IP VE.....	11
Configuring TSO support.....	11
Increasing disk space for BIG-IP VE.....	11
Updating BIG-IP VE.....	13
Updating BIG-IP VE.....	13
Download and import a BIG-IP VE update.....	13
Install a BIG-IP VE update.....	13
Reboot after a BIG-IP VE update.....	14
Legal Notices.....	15
Legal notices.....	15

Getting Started with BIG-IP Virtual Edition on Xen Project

Steps to deploy BIG-IP VE

To deploy the BIG-IP® Virtual Edition (VE) system on Xen Project, you will perform these tasks.

Step	Details
1	Choose the license you want to buy, the BIG-IP VE modules you want, and the throughput you need. See <i>SOL14810: Overview of BIG-IP® VE license and throughput limits</i> on the AskF5™ Knowledge Base (http://support.f5.com) for details.
2	Confirm that you are running a hypervisor version that is compatible with a BIG-IP VE release. See <i>Virtual Edition and Supported Hypervisors Matrix</i> on http://support.f5.com for details.
3	Verify that the host hardware meets the recommended requirements.
4	If you plan to use SR-IOV, enable it on the hypervisor.
5	Download a BIG-IP VE image and deploy it.
6	Assign a management IP address to the virtual machine.

After you complete these tasks, you can log in to the BIG-IP VE system and run the Setup utility to perform basic network configuration.

Prerequisites for BIG-IP Virtual Edition on Xen Project

Host CPU requirements

The host hardware CPU must meet the following requirements.

- The CPU must have 64-bit architecture.
- The CPU must have virtualization support (AMD-V or Intel VT-x) enabled.
- The CPU must support a one-to-one, thread-to-defined virtual CPU ratio, or on single-threading architectures, support at least one core per defined virtual CPU.
- If your CPU supports the Advanced Encryption Standard New Instruction (AES-NI), SSL encryption processing on BIG-IP® VE will be faster. Contact your CPU vendor for details about which CPUs provide AES-NI support.

Host memory requirements

The number of licensed TMM cores determines how much memory the host system requires.

Number of cores	Memory required
1	2 Gb
2	4 Gb
4	8 Gb
8	16 Gb

Configuring SR-IOV on the hypervisor

To increase performance, you can enable Single Root I/O Virtualization (SR-IOV). You need an SR-IOV-compatible network interface card (NIC) installed and the SR-IOV BIOS must be enabled.

See the Xen Project documentation for details.

To complete SR-IOV configuration, after you deploy BIG-IP® VE, you must add three PCI device NICs and map them to your networks.

Virtual machine memory requirements

The guest should have a minimum of 4 GB of RAM for the initial 2 virtual CPUs. For each additional CPU, you should add an additional 2 GB of RAM.

If you license additional modules, you should add memory.

Provisioned memory	Supported modules	Details
4 GB or fewer	Two modules maximum.	AAM can be provisioned as standalone only.
4-8 GB	Three modules maximum.	BIG-IP® DNS does not count toward the module limit.

Provisioned memory	Supported modules	Details
		Exception: Application Acceleration Manager™ (AAM®) cannot be provisioned with any other module; AAM is standalone only.
8 GB	Three modules maximum.	BIG-IP DNS does not count toward the module-combination limit.
12 GB or more	All modules.	N/A

Important: To achieve licensing performance limits, all allocated memory must be reserved.

Virtual machine storage requirements

The BIG-IP® modules you want to use determine how much storage the guest needs.

Provisioned storage	Supported modules	Details
8 GB	Local Traffic Manager™ (LTM®) module only; no space for LTM upgrades.	You can increase storage if you need to upgrade LTM or provision additional modules.
38 GB	LTM module only; space for installing LTM upgrades.	You can increase storage if you decide to provision additional modules. You can also install another instance of LTM on a separate partition.
139 GB	All modules and space for installing upgrades.	The Application Acceleration Manager™ (AAM®) module requires 20 GB of additional storage dedicated to AAM. For information about configuring the Datastore volume, see <i>Disk Management for Datastore</i> on the AskF5™ Knowledge Base (http://support.f5.com) for details.

For production environments, virtual disks should be deployed Thick (allocated up front). Thin deployments are acceptable for lab environments.

Note: To change the disk size after deploying the BIG-IP system, see *Increasing disk space for BIG-IP® VE*.

Virtual machine network interfaces

When you deploy BIG-IP® VE, a specific number of virtual network interfaces (vNICs) are available.

For Xen Project, three virtual NICs are required, at a minimum. More NICs are required if the high availability option is configured.

Each virtual machine can have a maximum of 10 NICs. You can deploy these as either:

- A management interface and 9 dataplane interfaces, or
- A management interface, 8 dataplane interfaces, and an HA interface.

Deploying BIG-IP Virtual Edition in Xen Project

Deploying BIG-IP VE on Xen Project

To deploy BIG-IP® VE in the open source Xen Project environment, you will create and execute a configuration file.

Important: Do not change the configuration (CPU, RAM, and network adapters) of the Xen Project guest environment with settings less powerful than those recommended and described here.

1. In a browser, open the F5 Downloads page (<https://downloads.f5.com>) and log in.
2. On the Downloads Overview page, select **Find a Download**.
3. Under Product Line, select **BIG-IP v12.x/Virtual Edition**.
4. Under Name, select **Virtual-Edition**.
5. If the End User Software License is displayed, read it and then click **I Accept**.
6. Download the BIG-IP VE file package ending with `qcow2.zip`.
7. Extract the file from the Zip archive and save it where your `qcow2` files reside on the Xen Project server.
8. Use VNC to access the Xen Project server, and then convert the `qcow2` image to the raw format necessary for Xen Project. You can use the following syntax to convert the image.
`# qemu-img convert <qcow_file_name>.qcow2 <raw_file_name>.raw`
9. Generate a MAC address for the network interface card associated with the management interface.

Important: Be sure that the MAC address you create starts with the prefix `00:16:3e:`.

You can use a tool such as MAC Address Generator (<http://www.miniwebtool.com/mac-address-generator/>) to create this address.

10. Use an editor to create a definition file that specifies the required parameters for your VM.
Use the following example to create a configuration file with the parameters and settings you need.

```
# vi /etc/xen/<config_file_name>
```

```
name = <config_file_name>
maxmem = 4096
memory = 4096
vcpus = 2
builder = "hvm"
boot = "c"
pae = 1
acpi = 1
apic = 1
hpet = 1
localtime = 0
on_poweroff = "destroy"
on_reboot = "restart"
on_crash = "restart"
sdl = 0
vnc = 1
vncunused = 1
keymap = "en-us"
disk = [ "file:/mnt/xen-bender/bigip/<raw_file_name.raw>,hda,w" ]
```

```
vif = [ "mac=00:16:<mgmt_interface_mac>,bridge=mgmtbr,script=vif-  
bridge,type=vif",  
       "mac=00:16:3e:<external_interface_mac>,bridge=ext_bridge,script=vif-  
bridge,type=vif",  
       "mac=00:16:3e:<internal_interface_mac>,bridge=int_bridge,script=vif-  
bridge,type=vif",]  
parallel = "none"  
serial = "pty"  
#pci = [ '05:10.0', '05:10.1' ]
```

Important: The last line of the example shows an optional entry, used for SR-IOV, with the IDs of the PCI external and internal network interface card (NIC). If you use this entry, omit the external and internal bridges specified in the `vif` section.

Once you have tested and saved your configuration file, you are ready to create the BIG-IP VE.

11. Run the configuration file using an open source tool such as `xm`.

```
xm create /etc/xen/<config_file_name>
```

If the startup was successful, the console will display text such as: Started domain

```
<config_file_name>(id=444).
```

12. Allow sufficient time for the boot-up process in order to connect to the BIG-IP VE console.

```
# xm console <config_file_name>
```

Accessing the BIG-IP VE management user interface

If your network has DHCP, an IP address is automatically assigned to BIG-IP® VE during deployment. You can use this address to access the BIG-IP VE user interface or `tmsh` command-line utility.

If no IP address was assigned, you can assign one by using the BIG-IP Configuration utility.

1. At the password prompt, type `default`.
2. Type `config` and press Enter.
The F5 Management Port Setup screen opens.
3. Click **OK**.
4. If you want DHCP to automatically assign an address for the management port, select **Yes**. Otherwise, select **No** and follow the instructions for manually assigning an IP address and netmask for the management port.

You can use a hypervisor generic statement, such as `tmsh show sys management-ip` to confirm that the management IP address has been properly assigned.

You can now log into the BIG-IP VE user interface, and license and provision BIG-IP VE.

After Deploying BIG-IP VE on Xen Project

About licensing BIG-IP VE

In order to use BIG-IP VE, you must have a license from F5. In the 12.x versions of BIG-IP, starting with BIG-IP VE version 12.1.3.1, you can revoke the license from a virtual machine and re-use it on another virtual machine.

From the Configuration utility, to revoke the license, go to **System > License** and click **Revoke**.

From tmsh, to revoke the license, run the command `tmsh revoke sys license`.

This functionality works for BIG-IP VE Bring Your Own License (BYOL) only.

Configuring TSO support

The TCP Segmentation Offloading (TSO) feature, which includes support for large receive offload (LRO) and Jumbo Frames, is enabled by default.

***Note:** You must have the admin user role to enable or disable TSO support.*

1. Use an SSH tool to access the BIG-IP® VE command line.
2. Log in as `root`.
3. Type `tmsh` to open the `tmsh` utility.
You will see `tmsh` at the prompt once the utility is opened.
4. To determine whether TSO support is currently enabled, use the command:
`show sys db tm.tcpsegmentationoffload`
5. To enable support for TSO, use the command:
`sys db tm.tcpsegmentationoffload enable`
6. To disable support for TSO, use the command:
`sys db tm.tcpsegmentationoffload disable`

Increasing disk space for BIG-IP VE

Before proceeding with these steps, use Virt Manager to expand the disk size for the BIG-IP® VE virtual machine and reboot.

Use the BIG-IP VE `tmsh` utility to increase the amount of disk space used by the four BIG-IP VE directories:

- `/config`
- `/shared`
- `/var`
- `/var/log`

***Note:** At the time of this release, decreasing the VE disk size is not supported.*

For each directory you want to resize, complete these steps.

1. Use an SSH tool to access the BIG-IP VE `tmsh` utility.

2. From the command line, log in as `root`.
3. List the current size of the directories on your disk so you can determine which ones need to be resized.

```
tmsh show sys disk directory
```
4. Expand the size of the directories in which you need additional space.

```
tmsh modify sys disk directory <directory name> new-size <new directory size in 1KB blocks>
```

For example, use `tmsh modify sys disk directory /config new-size 3145740` to increase the size of `/config` directory to 3145740 1KB blocks (or roughly 3,221,237,760 bytes).
5. To confirm that the command you just submitted is properly scheduled, you can show the new list of directories again.

```
tmsh show sys disk directory
```
6. If you change your mind about a submitted size change, you can revoke the size change.

```
tmsh modify sys disk directory /config new-size 0
```

In this example, the size of the `/config` directory is left as is, revoking any scheduled size changes. After you submit this sequence of `tmsh` commands, the directory size changes will be scheduled to occur the next time the BIG-IP VE virtual machine (VM) is rebooted.

The next time the VM running BIG-IP VE reboots, the changes are applied.

Updating BIG-IP VE

Updating BIG-IP VE

You do not need to reinstall BIG-IP® VE in order to install updates. You can use the Software Management tool in the Configuration utility, or you can upgrade the software from the command line.

To update BIG-IP VE, you will:

1. Download the ISO and MD5 files.
2. Install the downloaded files to an inactive boot location.
3. Boot the BIG-IP VE to the new boot location.

Download and import a BIG-IP VE update

To install an update, BIG-IP software needs access to the ISO file. If the update is a hotfix, you need the ISO files for both the base version and the hotfix.

1. In a browser, open the F5® Downloads page (<https://downloads.f5.com>).
2. Download the version's base ISO file and its associated MD5 checksum file.
3. Download the update ISO file and its associated MD5 checksum file.

Important: Before you perform the installation, you should test the integrity of the ISO files to verify that you have downloaded clean copies. Use an MD5 verification program to ensure that the downloaded ISO files' checksums match the values in their corresponding MD5 files.

4. In the BIG-IP VE user interface, on the Main tab, click **System > Software Management > Image List > Import**.
5. Click **Browse** to navigate to the downloaded base level installation file.
6. When the image name appears in the **Software Image** field, click **Import** to begin the operation.

Important: Do not navigate away from this screen before the operation is done.

When the import is complete, the Import page closes and the downloaded base image displays as an available image.

7. Click the Hotfix List tab.
8. At the right side of the screen, click **Import**.
9. Click **Browse** to navigate to the downloaded hotfix installation file.
10. When the image name appears in the **Software Image** field, click **Import** to begin the operation.

Important: Do not navigate away from this screen before the operation is done.

When the import is complete, the Import page closes and the downloaded hotfix displays in the list of available images.

You can now install the downloaded update.

Install a BIG-IP VE update

After you download and import the software installation image, you can initiate the installation operation. There are three boot locations on which you can install images on the BIG-IP® system. The process for installing a hotfix or a base version is essentially the same.

1. On the Main tab, click **System > Software Management**.
The Software Management Image List screen opens.
2. In the Available Images area, select the software image you want to install and click **Install**.
The Install Software Image popup screen opens.
3. Select the disk you want to install the image on, and then type or select a volume name, and click **Install**.

The upgrade process installs the software on the inactive disk location that you specify. This process usually takes between three and ten minutes.

***Tip:** If there is a problem during installation, you can use log messages to troubleshoot a solution. The system stores the installation log file as `/var/log/liveinstall.log`.*

The software image is installed.

When the installation operation is complete, you can safely reboot the newly installed volume or partition.

Reboot after a BIG-IP VE update

When the installation operation is complete, you can safely reboot into the newly installed volume or partition.

1. On the Main tab, click **System > Software Management**.
The Software Management Image List screen opens.
2. On the menu bar, click **Boot Locations**.
The Boot Locations screen opens.
3. In the Boot Location column, click the link representing the boot location you want to activate.
The properties screen for the boot location opens.
4. Click **Activate**.
A confirmation screen opens.
5. Click **OK** to initiate the reboot operation.
The system presents progress messages during the restart operation.

When the BIG-IP® VE system reboot is complete, the system presents the login screen. To configure the system, log in using an account that has administrative permissions.

Legal Notices

Legal notices

Publication Date

This document was published on April 26, 2018.

Publication Number

MAN-0472-05

Copyright

Copyright © 2018, F5 Networks, Inc. All rights reserved.

F5 Networks, Inc. (F5) believes the information it furnishes to be accurate and reliable. However, F5 assumes no responsibility for the use of this information, nor any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent, copyright, or other intellectual property right of F5 except as specifically described by applicable user licenses. F5 reserves the right to change specifications at any time without notice.

Trademarks

For a current list of F5 trademarks and service marks, see <http://www.f5.com/about/guidelines-policies/trademarks>.

All other product and company names herein may be trademarks of their respective owners.

Patents

This product may be protected by one or more patents indicated at: <https://f5.com/about-us/policies/patents>.

Export Regulation Notice

This product may include cryptographic software. Under the Export Administration Act, the United States government may consider it a criminal offense to export this product from the United States.

Index

B

BIG-IP VE
 deploying in Xen Project [9](#)
 BIG-IP Virtual Edition
 updating [13](#)

D

deployment overview [5](#)
 disk size, See virtual disk size
 downloads
 and importing update [13](#)
 of ISO base file [13](#)
 of ISO update file [13](#)

G

guest memory [7](#)

H

hypervisor
 configuring for SR-IOV [7](#)
 configuring for TSO [11](#)

I

installation
 rebooting after [14](#)
 installation operation [13](#)
 ISO file
 and location on virtual machine [13](#)
 downloading [13](#)
 downloading base file [13](#)
 downloading update file [13](#)

L

licensing BIG-IP VE [11](#)
 log file
 and location [13](#)
 and media speed messages [13](#)
 log in
 after updating [14](#)

M

memory
 guest [7](#)

R

reboot operation
 after updating [14](#)

S

SR-IOV
 configuring hypervisor for [7](#)
 system update procedure [13](#)

T

task list
 for updating on virtual machine [13](#)
 TSO support
 configuring hypervisor for [11](#)

U

update
 downloading and importing [13](#)
 installing [13](#)

V

virtual disk size
 extending [11](#)
 increasing [11](#)

X

Xen Project virtual machine
 creating [9](#)

